

SUPERFAST RECOVERY RECTIFIERS

VOLTAGE 50 to 800 Volts CURRENT 1.0 Ampere

FEATURES

- Plastic package has Underwriters Laboratories Flammability Classification 94V-O utilizing Flame Retardant Epoxy Molding Compound.
- Superfast recovery times-epitaxial construction.
- · Low forward voltage, high current capability.
- Exceeds environmental standards of MIL-S-19500/228.
- · Hermetically sealed.
- · Low leakage.
- High surge capability.
- Lead free in compliance with EU RoHS 2.0
- Green molding compound as per IEC 61249 standard


MECHANICAL DATA

• Case: Molded plastic, DO-41

• Terminals : Axial leads, solderable to MIL-STD-750, Method 2026

• Polarity: Color Band denotes cathode end.

Mounting Position : AnyApprox. Weight : 0.336 gram



MAXIMUM RATINGS AND ELECTRICAL CHARACTERISTICS

Ratings at 25°C ambient temperature unless otherwise specified.

Resistive or inductive load, 60Hz.

PARAMETER	SYMBOL	ER100	ER101	ER101A	ER102	ER103	ER104	ER106	ER108	UNITS
Maximum Recurrent Peak Reverse Voltage	V _{RRM}	50	100	150	200	300	400	600	800	V
Maximum RMS Voltage	V _{RMS}	35	70	105	140	210	280	420	560	٧
Maximum DC Blocking Voltage	V _{DC}	50	100	150	200	300	400	600	800	V
Maximum Average Forward Current .375"(9.5mm) lead length at T _A =55°C	I _{F(AV)}	1.0					Α			
Peak Forward Surge Current : 8.3ms single half sine-wave superimposed on rated load(JEDEC method)	I _{FSM}	30					Α			
Maximum Forward Voltage at 1.0A	V _F		0	0.95 1.25 1.7 2.			2.5	٧		
Maximum DC Reverse Current T _J =25°C at Rated DC Blocking Voltage T _J =100°C	I _R	1.0 150					μА			
Typical Junction capacitance (Note 2)	C¹	17					pF			
Maximum Reverse Recovery Time (Note 1)	t _{rr}	35					ns			
Typical Thermal Resistance	$R_{_{\theta JA}}$	50					°C / W			
Operating Junction and Storage Temperature Range	T_J, T_{STG}	-55 to +150					°C			

NOTES:

- 1. Reverse Recovery Test Conditions: I_F=.5A, I_R=1A, Irr=.25A
- 2. Measured at 1 MHz and applied reverse voltage of 4.0 VDC



RATING AND CHARACTERISTIC CURVES




FIG.1 TYPICAL JUNCTION CAPACITANCE




FIG.2 MAXIMUM AVERAGE FORWARD CURRENT DERATING




FIG.3 TYPICAL REVERSE CHARACTERISTICS





FIG.4 TYPICAL FORWARD CHARACTERISTICS






Product and Packing Information

Part No.	Package Type	Packing Type	Marking	
ER100	DO-41	5K pcs / Ammo	ER100	
ER101	DO-41	5K pcs / Ammo	ER101	
ER101A	DO-41	5K pcs / Ammo	ER101A	
ER102	DO-41	5K pcs / Ammo	ER102	
ER103	DO-41	5K pcs / Ammo	ER103	
ER104	DO-41	5K pcs / Ammo	ER104	
ER106	DO-41	5K pcs / Ammo	ER106	
ER108	DO-41	5K pcs / Ammo	ER108	

Packaging Information





Disclaimer

- Reproducing and modifying information of the document is prohibited without permission from Panjit International Inc..
- Panjit International Inc. reserves the rights to make changes of the content herein the document anytime without notification. Please refer to our website for the latest document.
- Panjit International Inc. disclaims any and all liability arising out of the application or use of any product including damages incidentally and consequentially occurred.
- Panjit International Inc. does not assume any and all implied warranties, including warranties
 of fitness for particular purpose, non-infringement and merchantability.
- Applications shown on the herein document are examples of standard use and operation.
 Customers are responsible in comprehending the suitable use in particular applications.
 Panjit International Inc. makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.
- The products shown herein are not designed and authorized for equipments requiring high level of reliability or relating to human life and for any applications concerning life-saving or life-sustaining, such as medical instruments, transportation equipment, aerospace machinery et cetera. Customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Panjit International Inc. for any damages resulting from such improper use or sale.
- Since Panjit uses lot number as the tracking base, please provide the lot number for tracking when complaining.